arXiv:math/0211009v1 [math.OC] 1 Nov 2002

Robust Strictly Positive Real Synthesis for Convex Combination of Sixth-Order Polynomials[1]

Wensheng YU

Institute of Automation, Chinese Academy of Sciences
Beijing 100080, CHINA. E-mail: wensheng.yu@mail.ia.ac.cn

Long WANG

Center for Systems and Control,
Department of Mechanics and Engineering Science, Peking University,
Beijing 100871, CHINA. E-mail: longwang@mech.pku.edu.cn

Abstract For the two sixth-order polynomials $a(s)$ and $b(s)$, Hurwitz stability of their convex combination is necessary and sufficient for the existence of a polynomial $c(s)$ such that $c(s)/a(s)$ and $c(s)/b(s)$ are both strictly positive real. Our reasoning method is constructive, and is insightful and helpful in solving the general robust strictly positive real synthesis problem.

Keywords Robust Stability, Strict Positive Realness, Robust Analysis and Synthesis

The strict positive realness (SPR) of transfer functions is an important performance specification, and plays a critical role in various fields such as absolute stability/hyperstability theory [12, 17], passivity analysis [9], quadratic optimal control [2] and adaptive system theory [13]. In recent years, stimulated by the parametrization method in robust stability analysis [3, 5], the study of robust strictly positive real systems has received much attention, and great progress has beem made [1, 4, 6, 7, 8, 10, 11, 14, 15, 16, 18, 19, 20, 21, 22, 23, 24, 25, 26, 27, 28, 29, 30]. However, most results belong to the category of robust SPR analysis. Valuable results in robust SPR synthesis are rare. The following fundamental problem is still open [1, 4, 8, 10, 11, 14, 15, 16, 18, 22, 24, 26, 27, 28, 29]:

Suppose $a(s)$ and $b(s)$ are two n-th order Hurwitz polynomials, does there exist, and how to find a (fixed) polynomial $c(s)$ such that $c(s)/a(s)$ and $c(s)/b(s)$ are both SPR?

By the definition of SPR, it is easy to know that the Hurwitz stability of the convex combination of $a(s)$ and $b(s)$ is necessary for the existence of polynomial $c(s)$ such that $c(s)/a(s)$ and $c(s)/b(s)$ are both SPR. In [10, 11, 16], it was proved that, if $a(s)$ and $b(s)$ have the same even (or odd) parts, such a polynomial $c(s)$ always exists; In [1, 10, 11, 14, 19, 20, 22, 23, 26, 27], it was proved that, if $n \leq 4$ and $a(s), b(s) \in K$ (K is a stable interval polynomial set), such a polynomial $c(s)$ always exists; Recent results show that [19, 20, 22, 23, 24, 26, 28, 29], if $n \leq 5$ and $a(s)$ and $b(s)$ are the two endpoints of the convex combination of stable polynomials, such a polynomial $c(s)$ always exists. Some sufficient condition for robust SPR synthesis are presented in [1, 4, 8, 14, 19, 20, 23], especially, the design method in [19, 20] is numerically efficient for high-order polynomial segments and interval polynomials, and the derived conditions are necessary and sufficient for low-order polynomial segments and interval polynomials.

This paper shows that, for the two sixth-order polynomials $a(s)$ and $b(s)$, Hurwitz stability of their convex combination is necessary and sufficient for the existence of a polynomial $c(s)$ such that $c(s)/a(s)$ and $c(s)/b(s)$ are both SPR. This also shows that the conditions given in [19, 20] are also

---

[1] Supported by National Natural Science Foundation of China and Natural Science Foundation of National Laboratory of Intelligent Technology and System of Tsinghua University.

necessary and sufficient, and the open problem above has a positive answer for the case of sixth-order polynomial segment. Our reasoning method is constructive, and is useful in solving the general robust SPR synthesis problem.

In this paper, P^n stands for the set of *n-th* order polynomials of s with real coefficients, R stands for the field of real numbers, $\partial(p)$ stands for the order of polynomial $p(\cdot)$, and $H^n \subset P^n$ stands for the set of *n-th* order Hurwitz stable polynomials with real coefficients.

In the following definition, $p(\cdot) \in P^m, q(\cdot) \in P^n, f(s) = p(s)/q(s)$ is a rational function.

Definition 1 [25] $f(s)$ is said to be strictly positive real(SPR), if

(i) $\partial(p) = \partial(q)$;

(ii) $f(s)$ is analytic in $\mathrm{Re}[s] \geq 0$, (namely, $q(\cdot) \in H^n$);

(iii) $\mathrm{Re}[f(j\omega)] > 0, \quad \forall \omega \in R$.

If $f(s) = p(s)/q(s)$ is proper, it is easy to get the following property:

Property 1 [7] If $f(s) = p(s)/q(s)$ is a proper rational function, $q(s) \in H^n$, and $\forall \omega \in R, \mathrm{Re}[f(j\omega)] > 0$, then $p(s) \in H^n \cup H^{n-1}$.

The following theorem is the main result of this paper:

Theorem 1 Suppose $a(s) = s^6+a_1s^5+a_2s^4+a_3s^3+a_4s^2+a_5s+a_6 \in H^6, b(s) = s^6+b_1s^5+b_2s^4+b_3s^3+b_4s^2+b_5s+b_6 \in H^6$, the necessary and sufficient condition for the existence of a polynomial $c(s)$ such that $c(s)/a(s)$ and $c(s)/b(s)$ are both Strictly Positive Real is

$$\lambda b(s) + (1-\lambda)a(s) \in H^6, \lambda \in [0, 1].$$

Since SPR transfer functions enjoy convexity property, by Property 1, we can easily get the necessary part of the theorem.

To prove sufficiency, we must first introduce some lemmas.

Lemma 1 Suppose $s^6 + a_1s^5 + a_2s^4 + a_3s^3 + a_4s^2 + a_5s + a_6 \in H^6$, then the following quadratic curve is an ellipse in the first quadrant of the *x-y-z-p* space:

$$\begin{cases} (a_2x + z - a_1y - a_3)^2 - 4(a_1 - x)(a_5 + a_3y + a_1p - a_2z - a_4x) = 0 \\ a_6x + a_4z - a_3p - a_5y = 0 \\ a_5p - a_6z = 0 \end{cases}$$

and this ellipse is tangent with the line

$$\begin{cases} a_6x + a_4z - a_3p - a_5y = 0 \\ a_5p - a_6z = 0 \\ a_1 - x = 0 \end{cases}$$

at

$$\begin{cases} x = a_1, \\ y = \frac{a_5a_6a_1 - a_5a_4a_2a_1 + a_5a_4a_3 + a_3a_6a_2a_1 - a_3^2a_6}{-a_5a_4a_1 + a_5^2 + a_3a_6a_1}, \\ z = -a_5\frac{a_5a_2a_1 - a_6a_1^2 - a_5a_3}{-a_5a_4a_1 + a_5^2 + a_3a_6a_1}, \\ p = -a_6\frac{a_5a_2a_1 - a_6a_1^2 - a_5a_3}{-a_5a_4a_1 + a_5^2 + a_3a_6a_1}, \end{cases}$$

tangent with the line

$$\begin{cases} a_6x + a_4z - a_3p - a_5y = 0 \\ a_5p - a_6z = 0 \\ a_5 + a_3y + a_1p - a_2z - a_4x = 0 \end{cases}$$

at

$$\begin{cases} x = \frac{-a_5^3+a_5^2a_4a_1+a_3^3a_6+a_5^2a_2a_3-a_5a_3^2a_4-2a_5a_3a_6a_1}{a_5^2a_2^2-a_5^2a_4+a_5a_4^2a_1-2a_5a_6a_1a_2-a_3a_6a_1a_4+a_6^2a_1^2+a_5a_3a_6-a_5a_3a_4a_2+a_3^2a_6a_2}, \\ y = \frac{a_6a_4a_3^2-a_3a_6^2a_1-a_3a_5a_4^2-a_5^2a_6+a_5^2a_4a_2}{a_5^2a_2^2-a_5^2a_4+a_5a_4^2a_1-2a_5a_6a_1a_2-a_3a_6a_1a_4+a_6^2a_1^2+a_5a_3a_6-a_5a_3a_4a_2+a_3^2a_6a_2}, \\ z = a_5\frac{a_2a_5^2-a_5a_6a_1-a_5a_4a_3+a_3^2a_6}{a_5^2a_2^2-a_5^2a_4+a_5a_4^2a_1-2a_5a_6a_1a_2-a_3a_6a_1a_4+a_6^2a_1^2+a_5a_3a_6-a_5a_3a_4a_2+a_3^2a_6a_2}, \\ p = a_6\frac{a_2a_5^2-a_5a_6a_1-a_5a_4a_3+a_3^2a_6}{a_5^2a_2^2-a_5^2a_4+a_5a_4^2a_1-2a_5a_6a_1a_2-a_3a_6a_1a_4+a_6^2a_1^2+a_5a_3a_6-a_5a_3a_4a_2+a_3^2a_6a_2}. \end{cases}$$

Proof Since $a(s)$ is Hurwitz stable, Lemma 1 is proved by a direct calculation.

Lemma 2 Suppose $s^6+a_1s^5+a_2s^4+a_3s^3+a_4s^2+a_5s+a_6 \in H^6$, then the following quadratic curve is an ellipse in the first quadrant of the x-y-z-p space:

$$\begin{cases} (a_5+a_3y+a_1p-a_2z-a_4x)^2-4(a_2x+z-a_1y-a_3)(a_6x+a_4z-a_3p-a_5y)=0 \\ a_1-x=0 \\ a_5p-a_6z=0 \end{cases}$$

and this ellipse is tangent with the line

$$\begin{cases} a_1-x=0 \\ a_5p-a_6z=0 \\ a_2x+z-a_1y-a_3=0 \end{cases}$$

at

$$\begin{cases} x=a_1, \\ y=\frac{-a_5^2+a_5a_4a_1-a_5a_2^2a_1+a_5a_2a_3+a_6a_1^2a_2-a_1a_6a_3}{-a_2a_1a_5+a_1^2a_6+a_3a_5}, \\ z=a_5\frac{a_3^2-a_3a_2a_1+a_4a_1^2-a_1a_5}{-a_2a_1a_5+a_1^2a_6+a_3a_5}, \\ p=a_6\frac{a_3^2-a_3a_2a_1+a_4a_1^2-a_1a_5}{-a_2a_1a_5+a_1^2a_6+a_3a_5}, \end{cases}$$

tangent with the line

$$\begin{cases} a_1-x=0 \\ a_5p-a_6z=0 \\ a_6x+a_4z-a_3p-a_5y=0 \end{cases}$$

at

$$\begin{cases} x=a_1, \\ y=\frac{a_4^2a_5a_1-a_3a_4a_1a_6-a_5^2a_4+a_3a_5a_6-a_2a_1a_5a_6+a_1^2a_6^2}{-a_5^2a_2+a_5a_4a_3-a_3^2a_6+a_5a_6a_1}, \\ z=a_5\frac{a_5a_4a_1-a_1a_6a_3-a_5^2}{-a_5^2a_2+a_5a_4a_3-a_3^2a_6+a_5a_6a_1}, \\ p=a_6\frac{a_5a_4a_1-a_1a_6a_3-a_5^2}{-a_5^2a_2+a_5a_4a_3-a_3^2a_6+a_5a_6a_1}.. \end{cases}$$

Proof Since $a(s)$ is Hurwitz stable, Lemma 2 is proved by a direct calculation.

Lemma 3 Suppose $s^6+a_1s^5+a_2s^4+a_3s^3+a_4s^2+a_5s+a_6 \in H^6$, then the following quadratic curve is an ellipse in the first quadrant of the x-y-z-p space:

$$\begin{cases} (a_6x+a_4z-a_3p-a_5y)^2-4(a_5+a_3y+a_1p-a_2z-a_4x)(a_5p-a_6z)=0 \\ a_1-x=0 \\ a_2x+z-a_1y-a_3=0 \end{cases}$$

and this ellipse is tangent with the line

$$\begin{cases} a_1 - x = 0 \\ a_2x + z - a_1y - a_3 = 0 \\ a_5 + a_3y + a_1p - a_2z - a_4x = 0 \end{cases}$$

at

$$\begin{cases} x = a_1, \\ y = -\frac{a_3a_5+a_3a_2^2a_1+a_1^2a_6-a_2a_3^2-a_4a_2a_1^2}{a_3^2-a_3a_2a_1+a_4a_1^2-a_1a_5}, \\ z = -\frac{a_2a_1a_3^2-a_2a_1^2a_5+2a_1a_3a_5+a_1^3a_6-a_3^3-a_3a_4a_1^2}{a_3^2-a_3a_2a_1+a_4a_1^2-a_1a_5}, \\ p = -\frac{2a_5a_4a_1+a_4a_1a_2a_3-a_5^2-a_5a_2^2a_1+a_5a_2a_3-a_1a_6a_3+a_6a_1^2a_2-a_4a_3^2-a_4^2a_1^2}{a_3^2-a_3a_2a_1+a_4a_1^2-a_1a_5}, \end{cases}$$

tangent with the line

$$\begin{cases} a_1 - x = 0 \\ a_2x + z - a_1y - a_3 = 0 \\ a_5p - a_6z = 0 \end{cases}$$

at

$$\begin{cases} x = a_1, \\ y = -\frac{a_5a_6a_1-a_5a_4a_2a_1+a_5a_4a_3+a_3a_6a_2a_1-a_3^2a_6}{a_5a_4a_1-a_1a_6a_3-a_5^2}, \\ z = -a_5\frac{-a_2a_1a_5+a_1^2a_6+a_3a_5}{a_5a_4a_1-a_1a_6a_3-a_5^2}, \\ p = -a_6\frac{-a_2a_1a_5+a_1^2a_6+a_3a_5}{a_5a_4a_1-a_1a_6a_3-a_5^2}. \end{cases}$$

Proof Since $a(s)$ is Hurwitz stable, Lemma 3 is proved by a direct calculation.

For notational simplicity, denote

$$\begin{aligned} \Omega_{e1}^a := \{(x,y,z,p)| \quad & (a_2x+z-a_1y-a_3)^2 - 4(a_1-x)(a_5+a_3y+a_1p-a_2z \\ & -a_4x) < 0, a_6x+a_4z-a_3p-a_5y = 0, a_5p-a_6z = 0\} \end{aligned}$$

$$\begin{aligned} \Omega_{e2}^a := \{(x,y,z,p)| \quad & (a_5+a_3y+a_1p-a_2z-a_4x)^2 - 4(a_2x+z-a_1y-a_3)(a_6x \\ & +a_4z-a_3p-a_5y) < 0, a_1-x = 0, a_5p-a_6z = 0\} \end{aligned}$$

$$\begin{aligned} \Omega_{e3}^a := \{(x,y,z,p)| \quad & (a_6x+a_4z-a_3p-a_5y)^2 - 4(a_5+a_3y+a_1p-a_2z \\ & -a_4x)(a_5p-a_6z) < 0, a_1-x = 0, a_2x+z-a_1y-a_3 = 0\} \end{aligned}$$

$$\begin{aligned} \Omega_{e1}^b := \{(x,y,z,p)| \quad & (b_2x+z-b_1y-b_3)^2 - 4(b_1-x)(b_5+b_3y+b_1p-b_2z \\ & -b_4x) < 0, b_6x+b_4z-b_3p-b_5y = 0, b_5p-b_6z = 0\} \end{aligned}$$

$$\begin{aligned} \Omega_{e2}^b := \{(x,y,z,p)| \quad & (b_5+b_3y+b_1p-b_2z-b_4x)^2 - 4(b_2x+z-b_1y-b_3)(b_6x \\ & +b_4z-b_3p-b_5y) < 0, b_1-x = 0, b_5p-b_6z = 0\} \end{aligned}$$

$$\begin{aligned} \Omega_{e3}^b := \{(x,y,z,p)| \quad & (b_6x+b_4z-b_3p-b_5y)^2 - 4(b_5+b_3y+b_1p-b_2z \\ & -b_4x)(b_5p-b_6z) < 0, b_1-x = 0, b_2x+z-b_1y-b_3 = 0\} \end{aligned}$$

In what follows, (A, B) stands for the set of points in the line segment connecting the point A and the point B in the x-y-z-p space, not including the endpoints A and B. Denote

$$\Omega^a := \{(x,y,z,p)|(x,y,z,p) \in (A,B) \cup (A,C) \cup (B,C), \forall A \in \Omega_{e1}^a, \forall B \in \Omega_{e2}^a, \forall C \in \Omega_{e3}^a\}$$

$$\Omega^b := \{(x,y,z,p)|(x,y,z,p) \in (A,B) \cup (A,C) \cup (B,C), \forall A \in \Omega_{e1}^b, \forall B \in \Omega_{e2}^b, \forall C \in \Omega_{e3}^b\}$$

Lemma 4 Suppose $a(s) = s^6 + a_1s^5 + a_2s^4 + a_3s^3 + a_4s^2 + a_5s + a_6 \in H^6, b(s) = s^6 + b_1s^5 + b_2s^4 + b_3s^3 + b_4s^2 + b_5s + b_6 \in H^6$, if $\Omega^a \cap \Omega^b \neq \phi$, take $(x,y,z,p) \in \Omega^a \cap \Omega^b$, and let $c(s) :=$

$s^5+(x-\varepsilon)s^4+ys^3+zs^2+ps+\varepsilon$ (ε is a sufficiently small positive number), then for $\dfrac{c(s)}{a(s)}$ and $\dfrac{c(s)}{b(s)}$, we have $\forall \omega \in R, \mathrm{Re}[\dfrac{c(j\omega)}{a(j\omega)}] > 0$ and $\mathrm{Re}[\dfrac{c(j\omega)}{b(j\omega)}] > 0$.

Proof Suppose $(x,y,z,p) \in \Omega^a \cap \Omega^b$, let $c(s) := s^5+(x-\varepsilon)s^4+ys^3+zs^2+ps+\varepsilon, \varepsilon > 0, \varepsilon$ sufficiently small.

$\forall \omega \in R$, consider

$$\begin{aligned}\mathrm{Re}[\frac{c(j\omega)}{a(j\omega)}] = \ & \frac{1}{\mid a(j\omega) \mid^2}[(a_1-x)\omega^{10}+(a_2x+z-a_1y-a_3)\omega^8+(a_5+a_3y+a_1p \\ & -a_2z-a_4x)\omega^6+(a_6x+a_4z-a_3p-a_5y)\omega^4+(a_5p-a_6z)\omega^2 \\ & +\varepsilon(\omega^{10}-a_2\omega^8+(a_4-1)\omega^6+(-a_6+a_2)\omega^4-a_4\omega^2+a_6)]\end{aligned}$$

In order to prove that $\forall \omega \in R, \mathrm{Re}[\dfrac{c(j\omega)}{a(j\omega)}] > 0$, let $t=\omega^2$, we only need to prove that, for any $\varepsilon > 0, \varepsilon$ sufficiently small, the following polynomial $f_1(t)$ satisfies

$$\begin{aligned}f_1(t) := \ & t[(a_1-x)t^4+(a_2x+z-a_1y-a_3)t^3+(a_5+a_3y+a_1p \\ & -a_2z-a_4x)t^2+(a_6x+a_4z-a_3p-a_5y)t+(a_5p-a_6z)] \\ & +\varepsilon(t^5-a_2t^4+(a_4-1)t^3+(-a_6+a_2)t^2-a_4t+a_6)] > 0, \quad \forall t \in [0,+\infty).\end{aligned}$$

Since $(x,y,z,p) \in \Omega^a$, by the definition of Ω^a, it is easy to know that

$$\begin{aligned}g_1(t) := \ & (a_1-x)t^4+(a_2x+z-a_1y-a_3)t^3+(a_5+a_3y+a_1p-a_2z-a_4x)t^2 \\ & +(a_6x+a_4z-a_3p-a_5y)t+(a_5p-a_6z) > 0, \quad \forall t \in [0,+\infty).\end{aligned}$$

Moreover, we obviously have $f_1(0) > 0$, and for any $\varepsilon > 0$, when t is a sufficiently large or sufficiently small positive number, we have $f_1(t) > 0$, namely, there exist $0 < t_1 < t_2$ such that, for all $\varepsilon > 0$, $t \in [0,t_1] \cup [t_2,+\infty)$, we have $f_1(t) > 0$.

Denote

$$M_1 = \inf_{t \in [t_1,t_2]} tg_1(t),$$

$$N_1 = \sup_{t \in [t_1,t_2]} |t^5-a_2t^4+(a_4-1)t^3+(-a_6+a_2)t^2-a_4t+a_6|.$$

Then $M_1 > 0$ and $N_1 > 0$. Choosing $0 < \varepsilon < \dfrac{M_1}{N_1}$, by a direct calculation, we have

$$\begin{aligned}f_1(t) := \ & t[(a_1-x)t^4+(a_2x+z-a_1y-a_3)t^3+(a_5+a_3y+a_1p \\ & -a_2z-a_4x)t^2+(a_6x+a_4z-a_3p-a_5y)t+(a_5p-a_6z)] \\ & +\varepsilon(t^5-a_2t^4+(a_4-1)t^3+(-a_6+a_2)t^2-a_4t+a_6) > 0, \quad \forall t \in [0,+\infty).\end{aligned}$$

Namely,

$$\forall \omega \in R, \mathrm{Re}[\frac{c(j\omega)}{a(j\omega)}] > 0.$$

Similarly, since $(x,y,z,p) \in \Omega^b$, there exist $0 < t_3 < t_4$ such that, for all $\varepsilon > 0$, $t \in [0,t_3] \cup [t_4,+\infty)$, we have $f_2(t) > 0$,where

$$\begin{aligned}f_2(t) := \ & t[(b_1-x)t^4+(b_2x+z-b_1y-b_3)t^3+(b_5+b_3y+b_1p \\ & -b_2z-b_4x)t^2+(b_6x+b_4z-b_3p-b_5y)t+(b_5p-b_6z)] \\ & +\varepsilon(t^5-b_2t^4+(b_4-1)t^3+(-b_6+b_2)t^2-b_4t+b_6)]\end{aligned}$$

Denote

$$\begin{aligned}g_2(t) := \ & (b_1-x)t^4+(b_2x+z-b_1y-b_3)t^3+(b_5+b_3y+b_1p-b_2z-b_4x)t^2 \\ & +(b_6x+b_4z-b_3p-b_5y)t+(b_5p-b_6z),\end{aligned}$$

$$M_2 = \inf_{t\in[t_3,t_4]} tg_2(t),$$

$$N_2 = \sup_{t\in[t_3,t_4]} |t^5 - b_2t^4 + (b_4-1)t^3 + (-b_6+b_2)t^2 - b_4t + b_6|.$$

Then $M_2 > 0$ and $N_2 > 0$. Choosing $0 < \varepsilon < \dfrac{M_2}{N_2}$, we have

$$\forall\omega \in R, \mathrm{Re}[\frac{c(j\omega)}{b(j\omega)}] > 0.$$

Thus, by choosing $0 < \varepsilon < \min\{\dfrac{M_1}{N_1}, \dfrac{M_2}{N_2}\}$, Lemma 4 is proved.

Lemma 5 Suppose $a(s) = s^6 + a_1s^5 + a_2s^4 + a_3s^3 + a_4s^2 + a_5s + a_6 \in H^6, b(s) = s^6 + b_1s^5 + b_2s^4 + b_3s^3 + b_4s^2 + b_5s + b_6 \in H^6$, if $\lambda b(s) + (1-\lambda)a(s) \in H^6, \lambda \in [0,1]$, then $\Omega^a \cap \Omega^b \neq \phi$

Proof If $\forall\lambda \in [0,1], a_\lambda(s) := \lambda b(s) + (1-\lambda)a(s) \in H^6$, by Lemmas 1-3, for any $\lambda \in [0,1]$, $\Omega^{a_\lambda}_{e1}, \Omega^{a_\lambda}_{e2}$ and $\Omega^{a_\lambda}_{e3}$ are three ellipses in the first quadrant of the *x*-*y*-*z*-*p* space, denote

$$\Omega^{a_\lambda} := \{(x,y,z,p)|(x,y,z,p) \in (A,B) \cup (A,C) \cup (B,C), \forall A \in \Omega^{a_\lambda}_{e1}, \forall B \in \Omega^{a_\lambda}_{e2}, \forall C \in \Omega^{a_\lambda}_{e3}\}.$$

Apparently, when λ changes continuously from 0 to 1, Ω^{a_λ} will change continuously from Ω^a to Ω^b, $\Omega^{a_\lambda}_{e1}$ will change continuously from Ω^a_{e1} to $\Omega^b_{e1}, \Omega^{a_\lambda}_{e2}$ will change continuously from Ω^a_{e2} to Ω^b_{e2}, and $\Omega^{a_\lambda}_{e3}$ will change continuously from Ω^a_{e3} to Ω^b_{e3}.

Now assume $\Omega^a \cap \Omega^b = \phi$, by the definitions of Ω^a and Ω^b, and Lemmas 1-3, $\exists u > 0$, $v > 0, u \neq a_1, u \neq b_1$, and $\exists k \in \{1,2,3\}$, such that the following plane in the *x*-*y*-*z*-*p* space

$$l: \quad \frac{x}{u} + \frac{y}{v} + \frac{z}{w} + \frac{p}{r} = 1$$

separates Ω^a and Ω^b, meanwhile, l is tangent with $\Omega^a_{e1}, \Omega^a_{e2}, \Omega^a_{e3}$ and Ω^b_{ek} simultaneously (or tangent with $\Omega^b_{e1}, \Omega^b_{e2}, \Omega^b_{e3}$ and Ω^a_{ek} simultaneously).

Without loss of generality, suppose that l is tangent with $\Omega^a_{e1}, \Omega^a_{e2}, \Omega^a_{e3}$ and Ω^b_{ek} simultaneously.

Since l is tangent with $\Omega^a_{e1}, \Omega^a_{e2}$ and Ω^a_{e3} simultaneously, $a(s)$ is Hurwitz stable and $u > 0, u \neq a_1, v > 0$, by a lengthy calculation, we get that the necessary and sufficient condition for l being tangent with $\Omega^a_{e1}, \Omega^a_{e2}$ and Ω^a_{e3} simultaneously is

$$uv^3 - a_1v^3 - a_2uv^2 + a_3v^2 + a_4uv - a_5v - a_6u = 0, w = -uv, r = -v^2 \tag{1}$$

Since $w = -uv, r = -v^2, l$ is tangent with Ω^b_{ek}, by a direct calculation, we have

$$uv^3 - b_1v^3 - b_2uv^2 + b_3v^2 + b_4uv - b_5v - b_6u = 0 \tag{2}$$

¿From (1) and (2), we obviously have $\forall\lambda \in [0,1]$,

$$uv^3 - a_{\lambda1}v^3 - a_{\lambda2}uv^2 + a_{\lambda3}v^2 + a_{\lambda4}uv - a_{\lambda5}v - a_{\lambda6}u = 0, w = -uv, r = -v^2 \tag{3}$$

where $a_{\lambda i} := a_i + \lambda(b_i - a_i), i = 1,2,3,4,5,6$. (3) shows that l is also tangent with $\Omega^{a_\lambda}_{ek} (\forall\lambda \in [0,1])$. But l separates Ω^a_{ek} and Ω^b_{ek}, and when λ changes continuously from 0 to 1, $\Omega^{a_\lambda}_{ek}$ will change continuously from Ω^a_{ek} to Ω^b_{ek}, which is obviously impossible. This completes the proof.

From Theorem 2.4 in [20], or the proof of Lemma 5 in [24], we have

Lemma 6 Suppose $a(s) = s^6 + a_1s^5 + a_2s^4 + a_3s^3 + a_4s^2 + a_5s + a_6 \in H^6, b(s) = s^6 + b_1s^5 + b_2s^4 + b_3s^3 + b_4s^2 + b_5s + b_6 \in H^6, c(s) = s^5 + xs^4 + ys^3 + zs^2 + ps + q$, if $\forall\omega \in R, \mathrm{Re}[\dfrac{c(j\omega)}{a(j\omega)}] > 0$ and $\mathrm{Re}[\dfrac{c(j\omega)}{b(j\omega)}] > 0$, take

$$\widetilde{c}\,(s) := c(s) + \delta \cdot d(s), \quad \delta > 0,\ \delta \text{ sufficiently small}$$

(where $d(s)$ is an arbitrarily given monic sixth-order polynomial), then $\dfrac{\widetilde{c}\,(s)}{a(s)}$ and $\dfrac{\widetilde{c}\,(s)}{b(s)}$ are both strictly positive real.

The sufficiency of Theorem 1 is now proved by combining Lemmas 1-6.

Remark 1 From the proof of Theorem 1, we can see that this paper not only proves the existence, but also provides a design method.

Remark 2 The method provided in this paper is constructive, and is insightful and helpful in solving the general robust SPR synthesis problem. This subject is currently under investigation.

Remark 3 Our results can easily be generalized to discrete-time case.

Remark 4 If $\dfrac{c(s)}{a(s)}$ and $\dfrac{c(s)}{b(s)}$ are both SPR, it is easy to know that $\forall \lambda \in [0, 1]$, $\dfrac{c(s)}{\lambda a(s) + (1-\lambda) b(s)}$ is also SPR.

Remark 5 The stability of polynomial segment can be checked by many efficient methods, e.g., eigenvalue method, root locus method, value set method, etc. [3, 5].

References

[1] Anderson, B. D. O., Dasgupta, S., Khargonekar, P., Kraus, F. J., and Mansou, M., Robust strict positive realness: characterization and construction, *IEEE Trans. Circuits Syst.*, 1990, CAS-37: 869-876.

[2] Anderson, B. D. O. and Moore, J. B., *Linear Optimal Control.* New York: Prentice Hall, 1970.

[3] Barmish, B. R., *New Tools for Robustness of Linear Systems.* New York: MacMillan Publishing Company, 1994.

[4] Betser, A. and Zeheb, E., Design of robust strictly positive real transfer functions. *IEEE Trans. Circuits Syst.; Part I,* 1993, **CAS-40:** 573-580.

[5] Bhattacharyya, S. P., Chapellat, H., and Keel, L . H .., *Robust Control: The Parametric Approach.* New York: Prentice Hall, 1995.

[6] Bianchini, G., Tesi, A., and Vicino, A., Synthesis of robust strictly positive real systems with l_2 parametric uncertainty. *IEEE Trans. Circuits Syst.; Part I,* 2001, **CAS-48:** 438-450.

[7] Chapellat, H., Dahleh, M., and Bhattacharyya, S. P., On robust nonlinear stability of interval control systems. *IEEE Trans. Automat. Contr.,* 1991, **AC-36:** 59-69.

[8] Dasgupta, S. and Bhagwat, A. S., Conditions for designing strictly positive real transfer functions for adaptive output error identification. *IEEE Trans. Circuits Syst.,* 1987, **CAS-34:** 731-737.

[9] Desoer, C. A., Vidyasagar, M. *Feedback Systems: Input-Output Properties.* San Diego: Academic Press, 1975.

[10] Hollot, C. V., Huang, L., and Xu, Z. L., Designing strictly positive real transfer function families: A necessary and sufficient condition for low degree and structured families. *Proc. of Mathematical Theory of Network and Systems,* (eds. Kaashoek, M. A., Van Schuppen, J. H., Ran, A. C. M.), Boston, Basel, Berlin: Birkhäuser, 1989, 215-227.

[11] Huang, L., Hollot, C. V., Xu, Z. L., Robust analysis of strictly positive real function set. Preprints of *The Second Japan-China Joint Symposium on Systems Control Theory and its Applications,* 1990, 210-220.

[12] Kalman, R. E., Lyapunov functions for the problem of Lur'e in automatic control. *Proc. Nat. Acad. Sci.*(USA), 1963, **49:** 201-205.

[13] Landau, I. D., *Adaptive Control: The Model Reference Approach.* New York: Marcel Dekker, 1979.

[14] Marquez, H. J. and Agathoklis, P., On the existence of robust strictly positive real rational functions. *IEEE Trans. Circuits Syst.; Part I,* 1998, **CAS-45:** 962-967.

[15] Mosquera, C. and Perez, F., Algebraic solution to the robust SPR problem for two polynomials. *Automatica,* 2001, **37:** 757-762.

[16] Patel, V. V. and Datta, K. B., Classification of units in H_∞ and an alternative proof of Kharitonov's theorem. *IEEE Trans. Circuits Syst.; Part I,* 1997, **CAS-44:** 454-458.

[17] Popov, V. M., *Hyperstability of Control Systems.* New York: Springer-Verlag, 1973.

[18] Wang, L. and Huang, L., Finite verification of strict positive realness of interval rational functions. *Chinese Science Bulletin,* 1991, **36:** 262-264.

[19] Wang, L. and Yu, W. S., A new approach to robust synthesis of strictly positive real transfer functions. *Stability and Control: Theory and Applications,* 1999, **2:** 13-24.

[20] Wang, L. and Yu, W. S., Complete characterization of strictly positive real regions and robust strictly positive real synthesis method. *Science in China,* 2000, **(E)43:** 97-112.

[21] Wang, L. and Yu, W. S., On robust stability of polynomials and robust strict positive realness of transfer functions. *IEEE Trans. on Circuits and Syst.; Part I,* 2001, **CAS-48:** 127-128.

[22] Wang, L. and Yu, W. S., Robust SPR synthesis for low-order polynomial segment and interval polynomials. *Proceedings of the American Control Conference (ACC 2001),* Crystal Gateway Marriott, Arlington, VA, USA, 2001, 3612-3617.

[23] Yu, W. S., *Robust Strictly Positive Real Synthesis and Robust Stability Analysis.* PhD Thesis, Peking University, Beijing, 1998.

[24] Yu, W. S. and Huang, L., A necessary and sufficient conditions on robust SPR stabilization for low degree systems. *Chinese Science Bulletin,* 1999, **44:** 517-520.

[25] Yu, W. S. and Wang, L., Some remarks on the definition of strict positive realness of transfer Functions. *Proceedings of Chinese Conference on Decision and Control,* Northeast University Press, Shenyang, 1999, 135-139.

[26] Yu, W. S. and Wang, L., Design of strictly positive real transfer functions. *IFAC Symposium on Computer Aided Control Systems Desgin (CACSD 2000),* Salford, UK, 2000.

[27] Yu, W. S. and Wang, L., Andersons's claim on fourth-order SPR synthesis is true. *IEEE Trans. Circuits Syst.; Part I,* 2001, **CAS-48:** 506-509.

[28] Yu, W. S. and Wang, L., Robust SPR synthesis for fourth-order convex combinations. *Progress in natural science,* 2001, **11:** 461-467.

[29] Yu, W. S. and Wang, L., Robust strictly positive real synthesis for convex combination of the fifth-order polynomials. *Proceedings of the IEEE Symposium on Circuits and Systems Conference (ISCAS 2001),* Sydney, Australia, 2001, Volume 1: 739-742.

[30] Yu, W. S., Wang, L., and Tan, M., Complete characterization of strictly positive realness regions in coefficient space. *Proceedings of the IEEE Hong Kong Symposium on Robotics and Control,* Hong Kong, 1999, 259-264.